



Features and Benefits

- Electronic Warfare
- Radar
- Communication links
- Test Instrumentation
- High Power Handling
- 67% operational bandwidth

Contact Us

978-772-7774

sales@rec-usa.com

www.rec-usa.com

12 Lancaster County Road

Harvard, MA 01451

Part number: 3A8BBB

6.0-12.0 GHz, Coaxial Circulator, X-band

For various applications including Electronic Warfare, Radar, Communication links and Test Instrumentation, Renaissance has designed a compact, High Power, Coaxial Circulator that can handle 150 watts CW over 6.0 – 12 GHz.

Specifications

Frequency	6.0 – 12.0 GHz
Insertion loss	0.6 dB
VSWR	1.30:1
Isolation	18 dB
Power	150 W CW
Temperature	-30°C to 80°C
Size	.75" x .75" x .5"