



Features and Benefits

- Electronic Warfare
- Radar
- Communication links
- Test Instrumentation
- High Power Handling
- 97% operational bandwidth

Contact Us

978-772-7774

sales@rec-usa.com

www.rec-usa.com

12 Lancaster County Road
Harvard, MA 01451

Part number: 3A9BBB

6.2-18 GHz, Coaxial Circulator, X-band

For various applications including Electronic Warfare, Radar, Communication links and Test Instrumentation, Renaissance has designed a compact, High Power, Coaxial Circulator that can handle 150 watts CW over 6.2 – 18 GHz.

Specifications

Frequency	6.2 – 18 GHz
Insertion loss	1.0 dB
VSWR	1.67:1
Isolation	12 dB
Power	150 W CW
Temperature	-40°C to 80°C
Size	.63" x .75" x .5"